

ANT-868-CW-RAH-SMA

✓ ACTIVE

TE Internal #: ANT-868-CW-RAH-SMA
Terminal/Duck Antenna, Single Band, LPWAN / LoRaWAN,
External Mount, Stud/Screw/Lug Mount, SMA, Omnidirectional,
Single Port, 0 < 3 dBi Peak Gain
[View on TE.com >](#)



Antennas



Communication Protocol: **LoRaWAN, LPWAN, Wi-Fi**
Mounting Location: **External**
Mounting Type: **Stud/Screw/Lug Mount**
Frequency Category: **862 – 870**
Antenna Type: **Terminal/Duck**

Features

Product Type Features

Antenna Termination	SMA
Antenna Product Type	Antenna

Configuration Features

Antenna Style	Whip
Mounting Location	External
Antenna Type	Terminal/Duck
Band Type	Single Band
Port Configuration	Single Port

Electrical Characteristics

Impedance	50 Ω
VSWR (Max)	<1.9:1

Signal Characteristics

Frequency Band	868 MHz
Frequency Category	862 – 870
Peak Gain	0 < 3 dBi

Body Features

Antenna Weight	6.13 g[.216 oz]
----------------	-----------------



Mechanical Attachment

Polarization	Linear
Mounting Type	Stud/Screw/Lug Mount

Dimensions

Product Width	16.1 mm[.63 in]
Product Length	47 mm[1.85 in]
Product Height	0 mm[0 in]

Operation/Application

Antenna Environment	Outdoor
Directionality	Omnidirectional

Industry Standards

Communication Protocol	LoRaWAN, LPWAN, Wi-Fi
Primary Application	LoRaWAN, LPWAN

Product Compliance

For compliance documentation, visit the product page on TE.com>

EU RoHS Directive 2011/65/EU	Compliant with Exemptions
EU ELV Directive 2000/53/EC	Not Yet Reviewed
China RoHS 2 Directive MIIT Order No 32, 2016	未针对中国 RoHS 符合性进行审核 Not reviewed for China RoHS compliance
EU REACH Regulation (EC) No. 1907/2006	Current ECHA Candidate List: JUNE 2025 (250) Not Yet Reviewed
Halogen Content	Not Yet Reviewed for halogen content
Solder Process Capability	Not reviewed for solder process capability

Product Compliance Disclaimer

This information is provided based on reasonable inquiry of our suppliers and represents our current actual knowledge based on the information they provided. This information is subject to change. The part numbers that TE has identified as EU RoHS compliant have a maximum concentration of 0.1% by weight in homogenous materials for lead, hexavalent chromium, mercury, PBB, PBDE, DBP, BBP, DEHP, DIBP, and 0.01% for cadmium, or qualify for an exemption to these limits as defined in the Annexes of Directive 2011/65/EU (RoHS2). Finished electrical and electronic equipment products will be CE marked as required by Directive 2011/65/EU. Components may not be CE marked. Additionally, the part numbers that TE has identified as EU ELV compliant have a maximum concentration of 0.1% by weight in homogenous materials for lead, hexavalent chromium, and mercury, and 0.01% for cadmium, or qualify for an exemption to these limits as defined in the Annexes of Directive 2000/53/EC (ELV). Regarding the REACH Regulations, TE’s information on SVHC in articles for this part number is still based on the European Chemical Agency (ECHA) ‘Guidance on requirements for substances in articles’(Version: 2, April 2011), applying the 0.1% weight on weight concentration threshold at the finished product level. TE is aware of the European Court of Justice ruling of September 10th, 2015 also known as O5A (Once An Article Always An Article) stating that, in case of ‘complex object’, the threshold for a SVHC must be applied to both the product as a whole and simultaneously to each of the articles forming part of its composition. TE has evaluated this ruling



based on the new ECHA “Guidance on requirements for substances in articles” (June 2017, version 4.0) and will be updating its statements accordingly.

Compatible Parts




TE Part # CONSMA002-SMD-G
SMA Jack 50 Ohm PCB Surface Mount



TE Part # CONSMA001
SMA Jack 50 Ohm PCB Through Hole



TE Part # CONSMA008-G
SMA Jack 50 Ohm Through Hole PCB



TE Part # CONSMA002-L-G
SMA Jack 50 Ohm PCB Through Hole

Customers Also Bought



TE Part #ANT-B5-CW-QW-SMA
Antenna 1/4 Wave Whip LTE B5 SMA



TE Part #ANT-916-CW-RAH-SMA
Antenna 1/4 Wave R-Angle 916MHz SMA



TE Part #ANT-868-PW-QW-UFL
Antenna 1/4 Wave Whip 868MHz 1.32 UFL



TE Part #ANT-DB1-LP-RM-01-N
Antenna Directional Tri-Band Hi-Gain N



TE Part #ANT-868-CW-RAH
Antenna 1/4 Wave R-Angle 868MHz RPS



TE Part #ANT-W63WS2-RPS
Antenna Blade Wifi6/6E Swivel RPS



TE Part #1623137-1
CRG0805 1% 1K5



TE Part #2195892-1
External Ant., SMA, 423-443MHz



TE Part #1-6609103-0
PE0SXDH6B=C1257



TE Part #L9000027-01
Antenna 1/2 Wave R-Angle 2.4GHz RPS

Documents

Product Drawings
Antenna 1/4 Wave R-Angle 868MHz SMA
English



CAD Files

Customer View Model

ENG_CVM_CVM_ANT-868-CW-RAH-SMA_A.2d_dxf.zip

English

3D PDF

3D

Customer View Model

ENG_CVM_CVM_ANT-868-CW-RAH-SMA_A.3d_igs.zip

English

Customer View Model

ENG_CVM_CVM_ANT-868-CW-RAH-SMA_A.3d_stp.zip

English

By downloading the CAD file I accept and agree to the [Terms and Conditions](#) of use.

Datasheets & Catalog Pages

ANT-868-CW-RAH-xxx

English