

ANT-868-CW-RCL-SMA

✓ ACTIVE

TE Internal #: ANT-868-CW-RCL-SMA
Terminal/Duck Antenna, Single Band, LPWAN / LoRaWAN,
External Mount, Stud/Screw/Lug Mount, SMA, Omnidirectional,
Single Port, 3 < 6 dBi Peak Gain
[View on TE.com >](#)



Antennas



Communication Protocol: **LoRaWAN, LPWAN, Wi-Fi**
Mounting Location: **External**
Mounting Type: **Stud/Screw/Lug Mount**
Frequency Category: **862 – 870**
Antenna Type: **Terminal/Duck**

Features

Product Type Features

Antenna Termination	SMA
Antenna Product Type	Antenna

Configuration Features

Antenna Style	Whip
Mounting Location	External
Antenna Type	Terminal/Duck
Band Type	Single Band
Port Configuration	Single Port

Electrical Characteristics

Impedance	50 Ω
VSWR (Max)	<1.9:1

Signal Characteristics

Frequency Band	868 MHz
Gain (Max)	4.1 dB
Frequency Category	862 – 870
Peak Gain	3 < 6 dBi

Mechanical Attachment

Polarization	Linear
--------------	--------



Mounting Type	Stud/Screw/Lug Mount
---------------	----------------------

Dimensions

Product Width	16.6 mm[.65 in]
Product Length	88 mm[3.46 in]
Product Height	0 mm[0 in]

Operation/Application

Antenna Environment	Outdoor
Directionality	Omnidirectional

Industry Standards

Communication Protocol	LoRaWAN, LPWAN, Wi-Fi
Primary Application	LoRaWAN, LPWAN

Product Compliance

For compliance documentation, visit the product page on TE.com>

EU RoHS Directive 2011/65/EU	Compliant with Exemptions
EU ELV Directive 2000/53/EC	Not Yet Reviewed
China RoHS 2 Directive MIIT Order No 32, 2016	未针对中国 RoHS 符合性进行审核 Not reviewed for China RoHS compliance
EU REACH Regulation (EC) No. 1907/2006	Current ECHA Candidate List: JUNE 2025 (250) Candidate List Declared Against: JUNE 2025 (250) SVHC > Threshold: Pb (4% in Component Part) Article Safe Usage Statements: Do not eat, drink or smoke when using this product. Wash thoroughly after handling. Recycle if possible and dispose of the article by following all applicable governmental regulations relevant to your geographic location.
Halogen Content	Low Halogen - Br, Cl, F < 900 ppm per homogenous material. Also BFR/CFR/PVC Free
Solder Process Capability	Not reviewed for solder process capability

Product Compliance Disclaimer

This information is provided based on reasonable inquiry of our suppliers and represents our current actual knowledge based on the information they provided. This information is subject to change. The part numbers that TE has identified as EU RoHS compliant have a maximum concentration of 0.1% by weight in homogenous materials for lead, hexavalent chromium, mercury, PBB, PBDE, DBP, BBP, DEHP, DIBP, and 0.01% for cadmium, or qualify for an exemption to these limits as defined in the Annexes of Directive 2011/65/EU (RoHS2). Finished electrical and electronic equipment products will be CE marked as required by Directive 2011/65/EU. Components may not be CE marked. Additionally, the part numbers that TE has identified as EU ELV compliant have a maximum concentration of 0.1% by weight in homogenous materials for lead, hexavalent chromium, and mercury, and 0.01% for cadmium, or qualify for an exemption to these limits as defined in the Annexes of Directive 2000/53/EC (ELV). Regarding the REACH Regulations, TE’s information on SVHC in



articles for this part number is still based on the European Chemical Agency (ECHA) ‘Guidance on requirements for substances in articles’(Version: 2, April 2011), applying the 0.1% weight on weight concentration threshold at the finished product level. TE is aware of the European Court of Justice ruling of September 10th, 2015 also known as O5A (Once An Article Always An Article) stating that, in case of ‘complex object’, the threshold for a SVHC must be applied to both the product as a whole and simultaneously to each of the articles forming part of its composition. TE has evaluated this ruling based on the new ECHA “Guidance on requirements for substances in articles” (June 2017, version 4.0) and will be updating its statements accordingly.

Compatible Parts



TE Part # ANT-868-CW-RCL
Antenna 1/2 Wave R-Angle 868MHz RPS




TE Part # CON SMA008-G
SMA Jack 50 Ohm Through Hole PCB



TE Part # CON SMA002-SMD-G
SMA Jack 50 Ohm PCB Surface Mount



TE Part # CON SMA001
SMA Jack 50 Ohm PCB Through Hole



TE Part # CON SMA002-L-G
SMA Jack 50 Ohm PCB Through Hole

Customers Also Bought



TE Part #ANT-868-CW-RCS-SMA
Antenna 1/4 Wave R-Angle 868MHz SMA



TE Part #ANT-868-CW-RCS
Antenna 1/4 Wave R-Angle 868MHz RPS



TE Part #8-1879343-8
CPF 0805 10K 1% 50PPM 1K RL



TE Part #2176412-3
5W XSM M/OX 5% 6R2



TE Part #1-2176412-0
5W XSM M/OX 5% 12R



TE Part #1-2176412-7
5W XSM M/OX 5% 24R



TE Part #2-2176412-5
5W XSM M/OX 5% 51R



TE Part #3-2176412-2
5W XSM M/OX 5% 100R

ANT-868-CW-RCL-SMA

Terminal/Duck Antenna, Single Band, LPWAN / LoRaWAN, External Mount, Stud /Screw/Lug Mount, SMA, Omnidirectional, Single Port, 3 < 6 dBi Peak Gain



Documents

Product Drawings

Antenna 1/2 Wave R-Angle 868MHz SMA

English

CAD Files

Customer View Model

ENG_CVM_CVM_ANT-868-CW-RCL-SMA_A.3d_stp.zip

English

Customer View Model

ENG_CVM_CVM_ANT-868-CW-RCL-SMA_A.2d_dxf.zip

English

Customer View Model

ENG_CVM_CVM_ANT-868-CW-RCL-SMA_A.3d_igs.zip

English

3D PDF

3D

By downloading the CAD file I accept and agree to the [Terms and Conditions](#) of use.

Datasheets & Catalog Pages

Linx RF Module Identification guide

English

868 MHz Right-Angle Whip Antenna

English

CW-RCL Series 868 MHz Right-Angle Whip Antenna

English